



W3-CV303HQ

Please adjust the four switches as below:



No.	Function Name	
1	AES	Auto Electronic Shutter On/Off
2	BLC	Backlight Compensation On/Off
3	AGC	Auto Gain Control On/Off
4	H-MIRROR	Horizontally Reverse Image On/Off

1. Auto Electronic Shutter On/Off Switch (AES): It's on when camera's manipulating or fixed aperture lens is used. This function makes image steady on the whole in spite of illumination's change.
2. Backlight Compensation On/Off Switch (BLC): It needs to be turned on when strong light at lobby door, windows and etc makes image dark and unclear. This function can help camera make a clear photo.
3. Auto Gain Control On/Off Switch (AGC):It can have camera work in a large range of illumination, help to high light camera's illumination and make a better image effect.
4. Horizontally Reverse Image On/Off Switch (H-MIRROR): That image level turns 180°makes camera's installation position more flexible.

Specifications:

Item No	W3-CV303HQ
Sensor	1/3 SONY CCD
TV System	PAL/NTSC
Sync	Internal
Resolution	540 Line
Lens	3.5 8mm
S/N ratio	48 dB(AGC OFF)
Mini Illumination	0 Lux
BLC	ON/OFF
AEC	ON/OFF
Voltage	DC 12V
Power Consumption	<250mA(DC 12V)
4 DIP	Yes
Operation temp	-10 °(To 50 °(Within85%RH)
Storage temp	-20 °(To 65 °(Within85%RH)
Dimension	150mm(H)×185.5mm(W)
Weight	1.1kg